

# WOYR2.E194579 - SWITCHES, APPLIANCE AND SPECIAL USE - COMPONENT

## Switches, Appliance and Special Use - Component

See General Information for Switches, Appliance and Special Use - Component

### E-SWITCH INC, DBA LAMB INDUSTRIES

7153 NORTHLAND DR N.  
BROOKLYN PARK, MN 55428 USA  
Investigated to ANSI/UL 61058-1

E194579




Cat. No.	Load	Amps	Volts	Hz	Temp (°C)	Pol/ Thr/ Cir	Endurance		Dis IP	Dis (mm)	SPCA	Std. Ed.
							30C cycle	55C cycle				
<b>Push Button</b>												
<b>HY106-6E7, HY106-6EB, HY106-6EC</b>												
	RM	18(18)	250	50-60	55	2/1-1.3	6K	50K	40	full 4.0	Note B	2005-09-30
<b>HY106-6Y7, HY106-6YB, HY106-6YC</b>												
	RM	18(18)	250	50-60	55	2/2-2.2	6K	50K	40	full 4.0	Note B	2005-09-30
<b>PV4F f/b 2 or 6, f/b 3, B, G, H, f/b 1, f/b numbers and letters</b>												
	GP	0.7	125	50-60	T55	1/2-1.2	6K	50K	--	full 1	Note A1, A2	-
<b>Rocker Switch</b>												
<b>R7 f/b 1 or 2, f/b 1,2,4,5,8 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters or numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T55	1/1-1.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
	R	16	30-6	DC	T55	1/2-2.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/1-1.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/2-2.2	6K	10K	67			

	RM	16(8)	125-250	50-60	T55	2/2-2.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	2/2-2.4	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/1-1.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/2-2.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-2.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-2.4	0K	10K	67			
	R	16	30-6	DC	T55	2/2-2.2	6K	10K	67			
	R	16	30-6	DC	T55	2/2-2.4	6K	10K	67			
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	15	30-6	DC	T85/55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	15	30-6	DC	T85/55	1/2-3.2	6K	10K	40	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	15	30-6	DC	T85/55	2/2-3.4	6K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	15	30-6	DC	T85/55	2/2-3.4	6K	10K	40	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T85/55	1/2-3.2	0K	10K	67	micro	7A, 7B,7C, 7D	-

<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T85/55	1/2-3.2	0K	10K	40	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T85/55	2/2-3.4	0K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T85/55	2/2-3.4	0K	10K	40	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	RM	16(8)	125-250	50-60	T85/55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	RM	16(8)	125-250	50-60	T85/55	1/2-3.2	6K	10K	40	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	RM	16(8)	125-250	50-60	T85/55	2/2-3.4	6K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	RM	20(8)	125-250	50-60	T55	1/2-3.2	0K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												

	RM	20(8)	125-250	50-60	T85/55	1/2-3.2	0K	10K	40	micro	7A, 7B,7C, 7D	-
	RM	20(8)	125-250	50-60	T85/55	2/2-3.4	0K	10K	40			
<b>R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers</b>												
	RM	20(8)	125-250	50-60	T55	2/2-3.4	0K	10K	67	micro	7A, 7B,7C, 7D	-
<b>R7 f/b 1 or 2, f/b 6, 7 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C 2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters or numbers, f/b letters or numbers, f/b letters or numbers</b>												
	R	16	30-6	DC	T55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
	R	16	30-6	DC	T55	2/2-3.4	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/2-3.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	2/2-3.4	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/2-3.2	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-3.4	6K	10K	67			
<b>RBW2A</b>	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
<b>RBW2A Illuminated</b>												
	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full	2, A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
<b>RBW2B</b>	hp	1/3	125	50	T85/55	2/2-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	RM	16(16)	125	50	T85/55	2/2-1.3	6K	50K	66			
<b>PP27H12A2, PP27H12B2, PP27H12C2, PP27H12D2</b>												
	RM	12(8)	127	50-60	T55	2/2-3.4	6K	50K	40	micro	17a	2005-09-30

Marking: Company name or trademark  ,  E-SWITCH<sup>®</sup> ,  , 

**LAMB** ,  **LAMB** ,  , catalog, model or part number, electrical ratings and the Recognized Component Mark,  on the product or on the smallest unit container in which the product is packaged.

Investigated to ANSI/UL 1054

Cat. No.	Amps	Volts	Hz	Load	Endur- ance	Temp C	POL/ THR	Per Pole/ Circuit Code	SPCOA
<b>HY11</b>	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
<b>HY12</b>	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
<b>HY15</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
<b>HY15B</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY15C</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
<b>HY18</b>	20	125	60	GP	6K	85	M/1	PP/-	-
	12	250	60	GP	6K				
<b>HY27</b>	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY27C</b>	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY30</b>	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
<b>HY34</b>	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
<b>HY37</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
<b>HY37B</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				

<b>HY37C</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
<b>HY38</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY38B</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY38C</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY42</b>	6	125	60	GP	6K	105	1/1	-/-	6 (18)
	3	250	60	GP	6K				
	1	125	DC	T	6K				
	6	125	60	L	6K				
<b>HY7-11D, HY7-41D, HY7-61D, HY7-81D, HY7-91D</b>									
	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
<b>HY7-12D, HY7-42D, HY7-62D, HY7-82D, HY7-92D</b>									
	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
<b>LSU11 Series</b>	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
<b>PA series</b>	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>PP1-1T7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
<b>PP1-DB7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-

	16	125	50/60	1hp	6K				
<b>PP1-DT7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
<b>PP1-EB7-xBx, PP1-EB7-xDx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
<b>PP1-FB7-xDx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
<b>PP2-1H7-xAx</b>	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
<b>PP2-1U7-xBx</b>	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
<b>PP2-4H7-xAx</b>	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
<b>PP2-4U7-xBx</b>	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
<b>PP2-4U7-xCx</b>	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
<b>PR Series</b>	16	125	60	GP	6K	105	2/2	-/-	2
	-	250	60	3/4hp	6K				
	-	125	60	1/2hp	6K				
<b>QKS-1</b>	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
<b>QKS-5</b>	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
<b>RA1</b>	16	125	60	GP	6K	105	1/1,1/2	-/-	-
	10	125	60	GP	6K				
	10	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA1-A, ww/o suffix letters and numbers</b>									
	11	125	60	GP	6K	55	2/M	-/-	-

	5.5	250	60	GP	6K				
<b>RA1-E ww/o suffix letters and numbers</b>									
	16	125	60	R	6K	55	M/1	PP/-	Note A1
<b>RA2 Series</b>	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA4 Series</b>	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA7 w/wo suffix letters and/or numbers, SP</b>									
	16	125	60	R	6K	55	1/1	-/-	A1
<b>RA8 Series, RR8 Series</b>	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA8-E ww/o suffix letters and numbers</b>									
	16	125	60	R	6K	55	M/1	PP/-	Note A1
<b>RA9 w/wo suffix letters and/or numbers, DP, SP</b>									
	16	125	60	R	6K	55	2/1	PP/-	A1
<b>RB1</b>	15	125	60	GP	6K	85	1/1,1/2	-/-	-
	7.5	250	60	GP	6K				
<b>RB1-D</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				



	-	250	60	3/4hp	6K				
<b>RB1-E</b>	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
<b>RB2-C[#], RB4-C[#]</b>	16	125	60	GP	6K	85	2/1, 2/2	-/-	2, 3
	8	250	60	GP	6K				
<b>RB2-D</b>	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RB2-E</b>	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
<b>RB2-H Series</b>	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RC SERIES f/b -1; f/b 1, 2 or 3 ; f/b 0, 1 or 3 ;f/b -C ;f/b 1, 2, 3, 4, 5, 6 or 7 ; f/b N or L; f/b- (letters; f/b letters; f/b H)or N); f/b (W); f/b -blank, -numbers or -letters.</b>									
	20	125	60	GP	12K	85	1/1	-/-	2, 3
	16	250	60	GP	12K				
	6	120	60	L	12K				
	-	250	60	3/4hp	12K				
<b>RD-Series</b>	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RE1-Series</b>	10	125	60	1/3hp	6K	105	1/2	PP/-	-
	10	250	60	1/3hp	6K				

	16	125	60	GP	6K				
<b>RF-SERIES</b>	16	125	60	GP	6K	105	2/1	PP/-	-
	-	125	60	1/2hp	6K				
	-	250	60	1/2hp	6K				
<b>RR Series</b>	10	125	60	1/3hp	6K	105	1/1	PP/-	-
	10	250	60	1/3hp	6K				
	16	125	60	GP	6K				
<b>RR5 f/b 0, 1 or 2, f/b -C or -R, f/b 1, 2, 3, 4, 5 or 6, f/b N, f/b -A, -B or -W f/b A, B, C, G, O, P, R, U, W or Y, f/b 1, 5, 6, 7</b>									
	20	125	60	GP	6K	65	1/M	-/-	Note 3
	12	250	60	GP	6K				
	12	125	60	GP	6K				
	10	250	60	GP	6K				
	10	125	60	GP	6K				
	6	250	60	GP	6K				
	6	125	60	GP	6K				
	3	250	60	GP	6K				
<b>RRA Series</b>	10	125	60	1/3hp	-	-	-	-/-	-
	10	250	60	1/3hp	-				
	15	125	60	GP	-				
<b>RSC Series</b>	15	125	60	GP	6K	105	1/1,1/2	-/-	-
	-	125	60	3/4hp	6K				
	20	125	60	GP	6K				
	-	-	-	GP	-				
<b>RSC-D</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-D2</b>	20	125	60	GP	6K	65	1/M	-/A	Note A2, A3
	16	125	60	GP	6K				

	16	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-H, RB1-H</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-X Series Where X denotes mfg.'s factory ID</b>									
	16	125	60	1/4hp	6K	65	1/M	-/-	3
	16	250	60	1/4hp	6K				
	20	125	60	3/4hp	6K				
	6.9	250	60	3/4hp	6K				
<b>RSC1 Series</b>	16	125	60	1/4hp	6K	65	1/M	-/-	3
	16	250	60	1/4hp	6K				
	6.9	250	60	3/4hp	6K				
	20	125	60	GP	6K				
<b>RV212, RV242, RV262, RV282, RV292</b>									
	20	125	60	GP	6K	65	2/1	PP/-	-
	12	250	60	GP	6K				
<b>RV213, RV243, RV263, RV283, RV293</b>									
	20	125	60	GP	6K	65	1/2	-/-	-
	12	250	60	GP	6K				
<b>RV216, RV246, RV266, RV286, RV296</b>									
	20	125	60	GP	6K	65	2/2	PP/-	-
	12	250	60	GP	6K				
<b>RV311, RV341, RV361, RV381, RV391</b>									
	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				

	10	125	60	R	6K				
	10	250	60	R	6K				
<b>RV312, RV342, RV362, RV382, RV392</b>									
	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
<b>ST113, ST123, ST143, ST163</b>									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST114, ST124, ST144, ST164</b>									
	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
<b>ST115, ST125, ST145, ST165</b>									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST16D</b>	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
<b>ST16M</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST16Z02</b>	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
<b>ST212, ST222, ST242, ST262</b>									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST216, ST226, ST246, ST266</b>									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				

<b>ST21G, ST22G, ST24G, ST26G, ST1W065, ST1W061</b>									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST26J</b>	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
<b>ST36T</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>WB242</b>	20	125	50/60	GP	6K	65	2/1	-/B	6
	20	250	50/60	GP	6K				
	-	125	50/60	2hp	-				
	-	250	50/60	2hp	-				
<b>WB246</b>	20	125	50/60	GP	6K	65	2/2	-/B	6
	20	250	50/60	GP	6K				
	-	125	-	2hp	6K				
	-	250	-	2hp	6K				
<b>WB24D</b>	20	125	50/60	GP	6K	65	1/2	-/A	6
	20	250	50/60	GP	6K				
	-	125	50/60	1- 1/2hp	-				
	-	250	50/60	1- 1/2hp	-				
<b>WB24E</b>	20	125	60	GP	6K	85	2/1	PP/-	-
	20	250	60	GP	6K				
	-	125	60	1- 1/2hp	6K				
	-	250	60	1- 1/2hp	6K				
<b>WB24G</b>	20	125	60	GP	6K	85	2/2	PP/-	-
	20	250	60	GP	6K				
	-	125	60	2hp	6K				
	-	250	60	2hp	6K				
<b>WB24H</b>	20	125	50/60	GP	6K	65	2/1	-/B	6

	20	250	50/60	GP	6K				
	-	125	50/60	1-1/2hp	-				
	-	250	50/60	1-1/2hp	-				
<b>WB24K</b>	20	125	60	GP	6K	85	2/2	PP/-	-
	20	250	60	GP	6K				
	-	125	60	1-1/2hp	6K				
	-	250	60	1-1/2hp	6K				
<b>WB2N42</b>	20	125	50/60	GP	6K	65	2/1	-/B	6
	20	250	50/60	GP	6K				
	-	125	50/60	2hp	-				
	-	250	50/60	2hp	-				

Note - n/a









Note 1 - These switches will require testing for horsepower ratings in the end-use product.

Note 2 - HY15B and HY37B: The lock-off mechanism on these switches has been evaluated.

Note 3 - Wire leads may be provided with the switches. The suitability of the wire size, temperature and voltage rating shall be evaluated in the end product. Also a Temperature Test shall be conducted in the end product.

x - Refers to the color, which can be black (1) or white (2) for all switches

[#] - indicates f/b 2 or 4, f/b 2 or G, followed by suffix letter C.

Marking: Company name or trademark  ,  E-SWITCH® ,  ,  ,  ,  ,  , catalog, model or part number, electrical ratings and the Recognized Component Mark,  on the product or on the smallest unit container in which the product is packaged.

Last Updated on 2019-02-01

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2019 UL LLC"