

WOYR2.E194579 - SWITCHES, APPLIANCE AND SPECIAL USE - COMPONENT

Switches, Appliance and Special Use - Component

See General Information for Switches, Appliance and Special Use - Component

E-SWITCH INC, DBA LAMB INDUSTRIES

7153 NORTHLAND DR N.
BROOKLYN PARK, MN 55428 USA
Investigated to ANSI/UL 61058-1

E194579




Cat. No.	Load	Amps	Volts	Hz	Temp (°C)	Pol/ Thr/ Cir	Endurance		Dis IP	Dis (mm)	SPCA	Std. Ed.
							30C cycle	55C cycle				
Push Button												
HY106-6E7, HY106-6EB, HY106-6EC												
	RM	18(18)	250	50-60	55	2/1-1.3	6K	50K	40	full 4.0	Note B	2005-09-30
HY106-6Y7, HY106-6YB, HY106-6YC												
	RM	18(18)	250	50-60	55	2/2-2.2	6K	50K	40	full 4.0	Note B	2005-09-30
PV4F f/b 2 or 6, f/b 3, B, G, H, f/b 1, f/b numbers and letters												
	GP	0.7	125	50-60	T55	1/2-1.2	6K	50K	--	full 1	Note A1, A2	-
Rocker Switch												
R7 f/b 1 or 2, f/b 1,2,4,5,8 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters or numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T55	1/1-1.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
	R	16	30-6	DC	T55	1/2-2.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/1-1.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/2-2.2	6K	10K	67			

	RM	16(8)	125-250	50-60	T55	2/2-2.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	2/2-2.4	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/1-1.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/2-2.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-2.2	0K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-2.4	0K	10K	67			
	R	16	30-6	DC	T55	2/2-2.2	6K	10K	67			
	R	16	30-6	DC	T55	2/2-2.4	6K	10K	67			
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	15	30-6	DC	T85/55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	15	30-6	DC	T85/55	1/2-3.2	6K	10K	40	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	15	30-6	DC	T85/55	2/2-3.4	6K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	15	30-6	DC	T85/55	2/2-3.4	6K	10K	40	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T85/55	1/2-3.2	0K	10K	67	micro	7A, 7B,7C, 7D	-

R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T85/55	1/2-3.2	0K	10K	40	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T85/55	2/2-3.4	0K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T85/55	2/2-3.4	0K	10K	40	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	RM	16(8)	125-250	50-60	T85/55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	RM	16(8)	125-250	50-60	T85/55	1/2-3.2	6K	10K	40	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	RM	16(8)	125-250	50-60	T85/55	2/2-3.4	6K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	RM	20(8)	125-250	50-60	T55	1/2-3.2	0K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												

	RM	20(8)	125-250	50-60	T85/55	1/2-3.2	0K	10K	40	micro	7A, 7B,7C, 7D	-
	RM	20(8)	125-250	50-60	T85/55	2/2-3.4	0K	10K	40			
R7 f/b 1 or 2, f/b 3 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters o numbers, f/b letters or numbers, f/b letters or numbers												
	RM	20(8)	125-250	50-60	T55	2/2-3.4	0K	10K	67	micro	7A, 7B,7C, 7D	-
R7 f/b 1 or 2, f/b 6, 7 f/b F,S or W, f/b A1, A2, A3, B1, B2, B3, B4, C1, C 2, C3 D1, D2, D3, E1, E2, E3, F1, f/b Sxxx, f/b letters or numbers, f/b letters or numbers, f/b B,D,2,4, f/b letters or numbers, f/b letters or numbers, f/b letters or numbers												
	R	16	30-6	DC	T55	1/2-3.2	6K	10K	67	micro	7A, 7B,7C, 7D	-
	R	16	30-6	DC	T55	2/2-3.4	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	1/2-3.2	6K	10K	67			
	RM	16(8)	125-250	50-60	T55	2/2-3.4	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	1/2-3.2	6K	10K	67			
	RM	20(8)	125-250	50-60	T55	2/2-3.4	6K	10K	67			
RBW2A	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
RBW2A Illuminated												
	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full	2, A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
RBW2B	hp	1/3	125	50	T85/55	2/2-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	RM	16(16)	125	50	T85/55	2/2-1.3	6K	50K	66			
PP27H12A2, PP27H12B2, PP27H12C2, PP27H12D2												
	RM	12(8)	127	50-60	T55	2/2-3.4	6K	50K	40	micro	17a	2005-09-30

Marking: Company name or trademark  ,  E-SWITCH[®] ,  , 

LAMB ,  **LAMB** ,  **LAMB INDUSTRIES** , catalog, model or part number, electrical ratings and the Recognized Component Mark,  on the product or on the smallest unit container in which the product is packaged.

Investigated to ANSI/UL 1054

Cat. No.	Amps	Volts	Hz	Load	Endur- ance	Temp C	POL/ THR	Per Pole/ Circuit Code	SPCOA
HY11	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
HY12	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
HY15	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
HY15B	18	125	60	GP	6K	65	M/M	PP/A	6 (12), Note 2
	12	250	60	GP	6K				
HY15C	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
HY18	20	125	60	GP	6K	85	M/1	PP/-	-
	12	250	60	GP	6K				
HY27	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
HY27C	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
HY30	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
HY34	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
HY37	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
HY37B	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				

HY37C	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
HY38	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY38B	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY38C	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY42	6	125	60	GP	6K	105	1/1	-/-	6 (18)
	3	250	60	GP	6K				
	1	125	DC	T	6K				
	6	125	60	L	6K				
HY7-11D, HY7-41D, HY7-61D, HY7-81D, HY7-91D									
	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
HY7-12D, HY7-42D, HY7-62D, HY7-82D, HY7-92D									
	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
LSU11 Series	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
PA series	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
PP1-1T7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-DB7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-

	16	125	50/60	1hp	6K				
PP1-DT7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-EB7-xBx, PP1-EB7-xDx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-FB7-xDx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP2-1H7-xAx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-1U7-xBx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4H7-xAx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4U7-xBx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4U7-xCx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PR Series	16	125	60	GP	6K	105	2/2	-/-	2
	-	250	60	3/4hp	6K				
	-	125	60	1/2hp	6K				
QKS-1	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
QKS-5	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
RA1	16	125	60	GP	6K	105	1/1,1/2	-/-	-
	10	125	60	GP	6K				
	10	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA1-A, ww/o suffix letters and numbers									
	11	125	60	GP	6K	55	2/M	-/-	-

	5.5	250	60	GP	6K				
RA1-E ww/o suffix letters and numbers									
	16	125	60	R	6K	55	M/1	PP/-	Note A1
RA2 Series	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA4 Series	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA7 w/wo suffix letters and/or numbers, SP									
	16	125	60	R	6K	55	1/1	-/-	A1
RA8 Series, RR8 Series	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA8-E ww/o suffix letters and numbers									
	16	125	60	R	6K	55	M/1	PP/-	Note A1
RA9 w/wo suffix letters and/or numbers, DP, SP									
	16	125	60	R	6K	55	2/1	PP/-	A1
RB1	15	125	60	GP	6K	85	1/1,1/2	-/-	-
	7.5	250	60	GP	6K				
RB1-D	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				

	-	250	60	3/4hp	6K				
RB1-E	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
RB2-C[#], RB4-C[#]	16	125	60	GP	6K	85	2/1, 2/2	-/-	2, 3
	8	250	60	GP	6K				
RB2-D	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RB2-E	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
RB2-H Series	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RC SERIES f/b -1; f/b 1, 2 or 3 ; f/b 0, 1 or 3 ;f/b -C ;f/b 1, 2, 3, 4, 5, 6 or 7 ; f/b N or L; f/b- (letters; f/b letters; f/b H)or N); f/b (W); f/b -blank, -numbers or -letters.									
	20	125	60	GP	12K	85	1/1	-/-	2, 3
	16	250	60	GP	12K				
	6	120	60	L	12K				
	-	250	60	3/4hp	12K				
RD-Series	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RE1-Series	10	125	60	1/3hp	6K	105	1/2	PP/-	-
	10	250	60	1/3hp	6K				

	16	125	60	GP	6K				
RF-SERIES	16	125	60	GP	6K	105	2/1	PP/-	-
	-	125	60	1/2hp	6K				
	-	250	60	1/2hp	6K				
RR Series	10	125	60	1/3hp	6K	105	1/1	PP/-	-
	10	250	60	1/3hp	6K				
	16	125	60	GP	6K				
RR5 f/b 0, 1 or 2, f/b -C or -R, f/b 1, 2, 3, 4, 5 or 6, f/b N, f/b -A, -B or -W f/b A, B, C, G, O, P, R, U, W or Y, f/b 1, 5, 6, 7									
	20	125	60	GP	6K	65	1/M	-/-	Note 3
	12	250	60	GP	6K				
	12	125	60	GP	6K				
	10	250	60	GP	6K				
	10	125	60	GP	6K				
	6	250	60	GP	6K				
	6	125	60	GP	6K				
	3	250	60	GP	6K				
RRA Series	10	125	60	1/3hp	-	-	-	-/-	-
	10	250	60	1/3hp	-				
	15	125	60	GP	-				
RSC Series	15	125	60	GP	6K	105	1/1,1/2	-/-	-
	-	125	60	3/4hp	6K				
	20	125	60	GP	6K				
	-	-	-	GP	-				
RSC-D	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RSC-D2	20	125	60	GP	6K	65	1/M	-/A	Note A2, A3
	16	125	60	GP	6K				

	16	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
	-	250	60	3/4hp	6K				
RSC-H, RB1-H	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RSC-X Series Where X denotes mfg.'s factory ID									
	16	125	60	1/4hp	6K	65	1/M	-/-	3
	16	250	60	1/4hp	6K				
	20	125	60	3/4hp	6K				
	6.9	250	60	3/4hp	6K				
RSC1 Series	16	125	60	1/4hp	6K	65	1/M	-/-	3
	16	250	60	1/4hp	6K				
	6.9	250	60	3/4hp	6K				
	20	125	60	GP	6K				
RV212, RV242, RV262, RV282, RV292									
	20	125	60	GP	6K	65	2/1	PP/-	-
	12	250	60	GP	6K				
RV213, RV243, RV263, RV283, RV293									
	20	125	60	GP	6K	65	1/2	-/-	-
	12	250	60	GP	6K				
RV216, RV246, RV266, RV286, RV296									
	20	125	60	GP	6K	65	2/2	PP/-	-
	12	250	60	GP	6K				
RV311, RV341, RV361, RV381, RV391									
	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				

	10	125	60	R	6K				
	10	250	60	R	6K				
RV312, RV342, RV362, RV382, RV392									
	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
ST113, ST123, ST143, ST163									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST114, ST124, ST144, ST164									
	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
ST115, ST125, ST145, ST165									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST16D	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
ST16M	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST16Z02	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
ST212, ST222, ST242, ST262									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST216, ST226, ST246, ST266									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				

ST21G, ST22G, ST24G, ST26G, ST1W065, ST1W061									
	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST26J	20	125	60	1- 1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1- 1/2hp	6K				
ST36T	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
WB242	20	125	50/60	GP	6K	65	2/1	-/B	6
	20	250	50/60	GP	6K				
	-	125	50/60	2hp	-				
	-	250	50/60	2hp	-				
WB246	20	125	50/60	GP	6K	65	2/2	-/B	6
	20	250	50/60	GP	6K				
	-	125	-	2hp	6K				
	-	250	-	2hp	6K				
WB24D	20	125	50/60	GP	6K	65	1/2	-/A	6
	20	250	50/60	GP	6K				
	-	125	50/60	1- 1/2hp	-				
	-	250	50/60	1- 1/2hp	-				
WB24E	20	125	60	GP	6K	85	2/1	PP/-	-
	20	250	60	GP	6K				
	-	125	60	1- 1/2hp	6K				
	-	250	60	1- 1/2hp	6K				
WB24G	20	125	60	GP	6K	85	2/2	PP/-	-
	20	250	60	GP	6K				
	-	125	60	2hp	6K				
	-	250	60	2hp	6K				
WB24H	20	125	50/60	GP	6K	65	2/1	-/B	6

	20	250	50/60	GP	6K				
	-	125	50/60	1- 1/2hp	-				
	-	250	50/60	1- 1/2hp	-				
WB24K	20	125	60	GP	6K	85	2/2	PP/-	-
	20	250	60	GP	6K				
	-	125	60	1- 1/2hp	6K				
	-	250	60	1- 1/2hp	6K				
WB2N42	20	125	50/60	GP	6K	65	2/1	-/B	6
	20	250	50/60	GP	6K				
	-	125	50/60	2hp	-				
	-	250	50/60	2hp	-				

Note - n/a









Note 1 - These switches will require testing for horsepower ratings in the end-use product.

Note 2 - HY15B and HY37B: The lock-off mechanism on these switches has been evaluated.

Note 3 - Wire leads may be provided with the switches. The suitability of the wire size, temperature and voltage rating shall be evaluated in the end product. Also a Temperature Test shall be conducted in the end product.

x - Refers to the color, which can be black (1) or white (2) for all switches

[#] - indicates f/b 2 or 4, f/b 2 or G, followed by suffix letter C.

Marking: Company name or trademark  ,  E-SWITCH® ,  ,  ,
 ,  ,  , catalog, model or part number, electrical ratings and the Recognized Component Mark,  on the product or on the smallest unit container in which the product is packaged.

Last Updated on 2019-02-01

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL's Follow-Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL's Follow-Up Service. Always look for the Mark on the product.

UL permits the reproduction of the material contained in the Online Certification Directory subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from the Online Certifications Directory with permission from UL" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "© 2019 UL LLC"