

Switches, Appliance and Special Use - Component

COMPANY

E-SWITCH INC, DBA LAMB INDUSTRIES
 7153 NORTHLAND DR N.
 BROOKLYN PARK, MN 55428 United States

E194579

Investigated to ANSI/UL 61058-1

Cat. No.	Load	Amps	Volts	Hz	Temp (°C)	Pol/	Endurance		Dis (mm)	SPCA	Std. Ed.	
						Cir	30C cycle	55C cycle				
Appliance Switches "T125/55"												
ST5 Series	R	16 PP	6-30	DC	T125/55	-1.4	6K	10K	40	micro	4A, 4B	-
	R	20 PP	6-30	DC	T125/55	-1.4	6K	10K	40			
	RM	16(8) PP	125/250	50-60	T125/55	-1.4	6K	10K	40			
	RM	20(8) PP	125/250	50-60	T125/55	-1.4	6K	10K	40			
Appliance Switches "T55"												
ST4 Series	-	PP	-	DC	55	-1.4	6K	10K	68	micro	-	-
	-	PP	-	DC	55	-1.4	6K	10K	-			
	GP	PP	-	50-60	55	-1.4	6K	10K	-			
	GP	PP	-	50-60	55	-1.4	6K	10K	-			
Appliance Switches												
14-RB1 Series	hp	3/4	125-250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125-250	60	55	1,2/1,2	6K	6K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(8)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125-250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125-250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
14-RB2 Series	hp	3/4	125-250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125-250	60	55	1,2/1,2	6K	6K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			

	RM	16(8)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125-250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125-250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
14-RSC Series	hp	3/4	125-250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125-250	60	55	1,2/1,2	6K	6K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(8)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125-250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125-250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
38-RB1 Series	R	0~20	125	50/60	105	1/1,2	6K	10K	40	full 1.5	-	-
	R	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~20	125	50/60	105	1/1,2	6K	10K	-			
	hp	3/4	125	50/60	105	1/1,2	6K	10K	-			
38-RB2 Series	R	0~16	125	50/60	T105	1,2/1,2	6K	10K	40	full 1.5	-	-
	GP	0~16	125	50/60	T105	1,2/1,2	6K	10K	-			
	hp	3/4	125	50/60	T105	1,2/1,2	6K	10K	-			
38-RSC Series	R	0~20	125	50/60	105	1/1,2	6K	10K	40	full 1.5	-	-
	R	0~15	125	50/60	105	1/1,2	6K	10K	-			

	GP	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~20	125	50/60	105	1/1,2	6K	10K	-			
	hp	3/4	125	50/60	105	1/1,2	6K	10K	-			
PP1-6	GP	-	-	50-60	T55	1/2-2.2	6K	50K	40	micro	-	-
PP1-7	GP	-	-	50-60	T55	1/2-2.2	6K	50K	40	micro	-	-
PR1 Series	hp	3/4	250	50/60	105	1,2/1	6K	10K	40	full	-	-
	hp	1/2	125	50/60	105	1,2/1	6K	10K	-			
	GP	16	125	50/60	105	1,2/1	6K	10K	-			
	R	16	125	50/60	105	1,2/1	6K	10K	-			
R7 f/b -1 or -2 f/b 3, f/b F,S or W, f/b Letter or Number. f/b Letter or Number. f/b Letter or Number. f/b Letter or Number. f/b -Letter or -Number. f/b Letter or Number.f/b A, B, D, 1, 2, 4, 7, 8 or 9. f/b -blank, -Letters or -Numbers	-	-	-	DC	40T85/55	1/2-3.2	6K	10K	40	micro	-	-
	-	-	-	DC	T85/55	1/2-3.2	6K	10K	40			
	-	-	-	DC	40T85/55	2/2-3.4	6K	10K	67			
	-	-	-	DC	T85/55	2/2-3.4	6K	10K	67			
	-	-	-	DC	T55	1/2-3.2	6K	10K	40			
	-	-	-	DC	T55	2/2-3.4	6K	10K	40			
	-	-	-	DC	40T85/55	1/2-3.2	-	10K	67			
	-	-	-	DC	T85/55	1/2-3.2	-	10K	67			
	-	-	-	DC	40T85/55	2/2-3.4	-	10K	40			
	-	-	-	DC	T85/55	2/2-3.4	-	10K	40			
	-	-	-	DC	T55	1/2-3.2	-	10K	67			
	-	-	-	DC	T55	2/2-3.4	-	10K	67			
	GP	-	-	50-60	40T85/55	1/2-3.2	6K	10K	40			
	GP	-	-	50-60	T85/55	1/2-3.2	6K	10K	40			
	GP	-	-	50-60	40T85/55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T85/55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	-			
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	-			
	GP	-	-	50-60	40T85/55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	T85/55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	40T85/55	2/2-3.4	-	10K	-			
	GP	-	-	50-60	T85/55	2/2-3.4	-	10K	-			
	GP	-	-	50-60	T55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	T55	2/2-3.4	-	10K	-			
R7 f/b 1 or 2 f/b 1,2,4,5 or 8, f/b F,S or W, f/b letter, f/b letter or number, f/b Sxxx, f/b letter or number, f/b letter or number, f/b A,B,D,1,2,4,7,8 or 9, f/b letter or number, f/b letter or number, f/b letters or numbers	R	16	30-6	DC	T55	1/1-1.2	6K	10K	-	micro	7A, 7B,7C, 7D. IP 40 for 40T85/55. IP 67 for T55	-
	R	16	30-6	DC	T55	1/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	1/1-1.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	1/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	2/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	2/2-2.4	6K	10K	-			

	RM	20(8)	125-250	50-60	T55	1/1-1.2	6K	10K	-			
	RM	20(8)	125-250	50-60	T55	1/2-2.2	6K	10K	-			
	RM	20(8)	125-250	50-60	T55	2/2-2.2	6K	10K	-			
	RM	20(8)	125-250	50-60	T55	2/2-2.4	6K	10K	-			
	R	16	30-6	DC	T55	2/2-2.2	6K	10K	-			
	R	16	30-6	DC	T55	2/2-2.4	6K	10K	-			
	R	16	30-6	DC	40T85/55	1/2, 2/2-2.2	6K	10K	-			
	R	16	30-6	DC	T85/55	1/2, 2/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	40T85/55	1/2, 2/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T85/55	1/2, 2/2-2.2	6K	10K	-			
	RM	20(8)	125-250	50-60	40T85/55	1/2, 2/2-2.2	-	10K	-			
	RM	20(8)	125-250	50-60	T85/55	1/2, 2/2-2.2	-	10K	-			
R7 f/b 1 or 2, f/b 6 or 7 f/b F,S or W, f/b letter, f/b letter or number, f/b Sxxx, f/b letter or number, f/b letter or number, f/b A,B,D,1,2,4,7,8 or 9, f/b letter or number, f/b letter or number, f/b letters or numbers.	-	-	-	DC	T55	1/2-3.2	6K	10K	67	micro	-	-
	-	-	-	DC	T55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	67			
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	67			
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	67			
	-	-	-	DC	40T85/55	1/2, 2/2-3.4	6K	10K	40			
	-	-	-	DC	T85/55	1/2, 2/2-3.4	6K	10K	40			
	GP	-	-	50-60	40T85/55	1/2, 2/2-3.4	6K	10K	40			
	GP	-	-	50-60	T85/55	1/2, 2/2-3.4	6K	10K	-			
	GP	-	-	50-60	40T85/55	1/2, 2/2-3.4	6K	10K	-			
	GP	-	-	50/60	T85/55	1/2, 2/2-3.4	6K	10K	-			
	GP	-	-	-	-	-	-	-	-			
	GP	-	-	-	-	-	-	-	-			
	GP	-	-	-	-	-	-	-	-			
RR1 followed by number, followed by 1, 3 or 5, followed by 3, maybe followed by alphanumeric/suffixes.	GP	-	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-
	GP	-	-	50/60	105	1,2/1,2	6K	10K	-			
RR1 followed by number, followed by 1, 3 or 5, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
RR8 followed by number, followed by number or letter, followed by 3, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			
RR8 followed by number, followed by number or letter, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			

	GP	PP	-	50/60	105	1,2/1	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1	6K	10K	-				
RRA followed by number, followed by number or letter, followed by 3, maybe followed by alphanumeric/suffixes.	GP	-	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	-	-	50/60	105	1,2/1,2	6K	10K	-				
RRA followed by number, followed by number or letter, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
RRG3 followed by number, followed by 1, 3 or 5, followed by 3, maybe followed by alphanumeric/suffixes.	R	10	125	50/60	105	1,2/1,2	6K	10K	40	full	2A	-	-
	GP	10	125	50/60	105	1,2/1,2	6K	10K	40				
RRG3 followed by number, followed by 1, 3 or 5, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
Micro													
PP2	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-	-
PP2-2	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-	-
PP2-3	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-	-
PP2-4	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-	-
PP2-5	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-	-
Push Button													
HY106-6E7, HY106-6EB, HY106-6EC	RM	18(18)	250	50-60	55	2/1-1.3	6K	50K	40	full 4.0	Note B		2005-09-30
HY106-6V7, HY106-6YB, HY106-6YC	RM	18(18)	250	50-60	55	2/2-2.2	6K	50K	40	full 4.0	Note B		2005-09-30
PA4 f/b none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C of J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8, f/b none or 1, f/b none, 0, 1, 2, 3, 4 or 5, f/b none, 3, 4, 5, 6 or 7	GP	16(4)	125	50-60	T125/55	1/1-1.2	6K	10K	-	full 3.1	6A, 8A, 8B, 8C	-	-
	GP	16(4) PP	125	50-60	T125/55	2/1-1.4	6K	10K	-				
	GP	16(8)	125	50-60	T125/55	1/1-1.2	6K	10K	-				
	GP	16(8) PP	125	50-60	T125/55	2/1-1.4	6K	10K	-				
	GP	16(4)	250	50-60	T125/55	1/1-1.2	6K	10K	-				
	GP	16(4) PP	250	50-60	T125/55	2/1-1.4	6K	10K	-				
	GP	16(8)	250	50-60	T125/55	1/1-1.2	6K	10K	-				
	GP	16(8) PP	250	50-60	T125/55	2/1-1.4	6K	10K	-				
	hp	1/4	125-250	60	T55	1/1,2/1	6K	6K	-				
	hp	3/4	125-250	60	T55	1/1,2/1	6K	6K	-				
PA5 f/b none or F, f/b 1 thru 6, 1, 4, 2 or E, f/b C or J	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40	full 3.1	-	-	-
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				

	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	60	T55	1/1,2/1	6K	6K	40				
	GP	-	-	60	T55	1/1,2/1	6K	6K	40				
PB66	RM	16(16)	127	50/60	T105/55	2/1-1.3	6K	50K	00	-	-	-	-
ULP Followed by 12, followed by OA, followed by M1 or P1, followed by R, followed by SS, SF, PM or LS, followed by CL1 or OP1, followed by NIL, BLU, GRN, RED, YEL or RGB, followed by NIL, BLU, GRN, RED, YEL.	R	0~0.1	0~28	DC	40T85	1/2-2.3	-	10K	40	full 0.8	1A	-	-
	R	0~0.1	0~28	DC	40T85	1/1-1.2	-	10K	-				
Reversing Polarity													
ST34RE00	GP	18(15) PP	125	50-60	55	M/M-1.6	6K	50K	-	full 1.5	6	-	-
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
ST34SE00	GP	PP	-	50-60	55	M/M-1.6	6K	50K	40	full 1.5	-	-	-
	GP	-	-	50/60	-	-	-	-	00				
	GP	-	-	50/60	-	-	-	-	00				
ST34TE00	GP	18(15) PP	125	50-60	55	M/M-1.6	6K	50K	-	full 1.5	6	-	-
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
Rocker													
RA1 (3 Series)	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/1,2	6K	10K	-				
RA1 (C Series)	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
RA4 (3 Series)	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/1,2	6K	10K	-				
RA4 (C Series)	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
RA8 (3 Series)	R	10 PP	125	50/60	105	1,2/1	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/1	6K	10K	-				
RA8 (C Series)	hp	1/3 PP	125	50/60	105	1,2/1	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1	6K	10K	-				
RB5 Series	RM	16(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	67	full	4A	-	-
	RM	20(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	-				

	RM	25(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	-				
	R	16	6~48	DC	T55	1,2/1,2-1.4	-	10K	-				
	R	20	6~36	DC	T55	1,2/1,2-1.4	-	10K	-				
RD1 (3 Series)	R	10 PP	125	50/60	105	1,2/1	6K	10K	40	full	-		-
	GP	10 PP	125	50/60	105	1,2/1	6K	10K	-				
RD1 (C Series)	hp	1/3 PP	125	50/60	105	1,2/1	6K	10K	40	full	-		-
	R	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1	6K	10K	-				
RE1 (3 Series)	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	GP	10 PP	125	50/60	105	1,2/1,2	6K	10K	-				
RE1 (C Series)	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
RRGA (3 Series)	R	10	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	GP	10	125	50/60	105	1,2/1,2	6K	10K	-				
ST121D00	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6		-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-				
ST123D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST124D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST125D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST12DD00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST141D00	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6		-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-				
ST143D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST144D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST144D10	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
ST145D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				

ST145D10	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST14DD00	GP	18(12)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6	-
	GP	18(12)	125	50-60	55	1/2-3.2	6K	50K	-			
ST14DD10	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST161D00	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6	-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-			
ST163D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST164D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST165D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST16DD00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST1W061D00	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
ST222D00	GP	18(15) PP	125	50-60	55	2/2-2.4	6K	50K	-	full 1.5	6	-
	GP	18(15) PP	125	50-60	55	2/1-1.4	6K	50K	-			
ST226D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST22ED00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST22GD00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST22KD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST242D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST246D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST24ED00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-

	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
ST24GD00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40				
ST24JD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
ST24KD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
ST24Z02D00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
ST262D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40				
ST266D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40				
ST266D02	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40				
ST26ED00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
ST26GD00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40				
ST26KD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-	
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40				
Rocker Switch													
RB3 Series	RM	16(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	67	full	4A		-
RBW2A	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full 2.0	A, B, C, D		2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66				
RBW2A Illuminated	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full	2, A, B, C, D		2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66				
RBW2B	hp	1/3	125	50	T85/55	2/2-1.3	6K	50K	66	full 2.0	A, B, C, D		2005-09-30
	RM	16(16)	125	50	T85/55	2/2-1.3	6K	50K	66				
PP27H12A2, PP27H12B2, PP27H12C2, PP27H12D2	RM	12(8)	127	50-60	T55	2/2-3.4	6K	50K	40	micro	17a		2005-09-30

Investigated to ANSI/UL 1054

Cat. No.	Amps	Volts	Hz	Load	Endur- ance	Temp (°C)	POL/ THR	Circuit Code	SPCOA
HY11	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
HY12	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
HY15	18	125	60	GP	6K	65	M/M	PP/A	6 (12)

	12	250	60	GP	6K				
HY15B	18	125	60	GP	6K	65	M/M	PP/A	6 (12), Note 2
	12	250	60	GP	6K				
HY15C	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
HY18	20	125	60	GP	6K	85	M/1	PP/-	-
	12	250	60	GP	6K				
HY27	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
HY27C	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
HY30	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
HY34	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
HY37	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
HY37B	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
HY37C	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
HY38	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY38B	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY38C	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
HY42	6	125	60	GP	6K	105	1/1	-/-	6 (18)
	3	250	60	GP	6K				
	1	125	DC	T	6K				
	6	125	60	L	6K				
HY7-11D, HY7-41D, HY7-61D, HY7-81D, HY7-91D	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
HY7-12D, HY7-42D, HY7-62D, HY7-82D, HY7-92D	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
LSU11 Series	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
PA series	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
PA4 Followed by none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8, f/b 1, f/b 0 thru 5, f/b 3 thru 7.	16	125	60	GP	6K	65	1/1 or 2/1	PP/A or D1	A2
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
	12	125	60	GP	6K				

	12	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
PA4 Followed by none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8.	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
	12	125	60	GP	6K				
	12	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
PA5 Followed by none or F, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J.	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
	12	125	60	GP	6K				
	12	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
PP1-1T7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-DB7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-DT7-xBx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-EB7-xBx, PP1-EB7-xDx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP1-FB7-xDx	12	250	50/60	1hp	6K	85	1/2	-/-	-
	16	125	50/60	1hp	6K				
PP2-1H7-xAx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-1U7-xBx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4H7-xAx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4U7-xBx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PP2-4U7-xCx	12	250	60	1hp	6K	85	2/2	-/-	-
	16	250	60	1hp	6K				
PR Series	16	125	60	GP	6K	105	2/2	-/-	2
	-	250	60	3/4hp	6K				
	-	125	60	1/2hp	6K				
QKS-1	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
QKS-5	12	125	60	GP	6K	65	2/1	PP/-	Note 1
	8	250	60	GP	6K				
RA1	16	125	60	GP	6K	105	1/1,1/2	-/-	-
	10	125	60	GP	6K				
	10	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				

RA1-A, ww/o suffix letters and numbers	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
RA1-E ww/o suffix letters and numbers	16	125	60	R	6K	55	M/1	PP/-	Note A1
RA2 Series	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA4 Series	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA7 w/wo suffix letters and/or numbers, SP	16	125	60	R	6K	55	1/1	-/-	A1
RA8 Series, RR8 Series	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
RA8-E ww/o suffix letters and numbers	16	125	60	R	6K	55	M/1	PP/-	Note A1
RA9 w/wo suffix letters and/or numbers, DP, SP	16	125	60	R	6K	55	2/1	PP/-	A1
RB1	15	125	60	GP	6K	85	1/1,1/2	-/-	-
	7.5	250	60	GP	6K				
RB1-D	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RB1-E	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
RB2-C	16	125	60	GP	6K	85	2/1, 2/2	-/-	2, 3
	8	250	60	GP	6K				
RB2-D	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RB2-E	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
RB2-H Series	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
RC SERIES	20	125	60	GP	12K	85	1/1	-/-	2, 3
	16	250	60	GP	12K				
	6	120	60	L	12K				
	-	250	60	3/4hp	12K				
RD-Series	10	125	60	GP	6K	105	1/1,2/1	-/-	-

	10	250	60	GP	6K					
	16	125	60	GP	6K					
	-	125	60	1/3hp	6K					
	-	250	60	1/3hp	6K					
RE1-Series	10	125	60	1/3hp	6K	105	1/2	PP/-	-	
	10	250	60	1/3hp	6K					
	16	125	60	GP	6K					
RF-SERIES	16	125	60	GP	6K	105	2/1	PP/-	-	
	-	125	60	1/2hp	6K					
	-	250	60	1/2hp	6K					
RR Series	10	125	60	1/3hp	6K	105	1/1	PP/-	-	
	10	250	60	1/3hp	6K					
	16	125	60	GP	6K					
RR5	20	125	60	GP	6K	65	1/M	-/-	Note 3	
	12	250	60	GP	6K					
	12	125	60	GP	6K					
	10	250	60	GP	6K					
	10	125	60	GP	6K					
	6	250	60	GP	6K					
	6	125	60	GP	6K					
	3	250	60	GP	6K					
RRA Series	10	125	60	1/3hp	-	-	-	-/-	-	
	10	250	60	1/3hp	-					
	15	125	60	GP	-					
RSC Series	15	125	60	GP	6K	105	1/1,1/2	-/-	-	
	-	125	60	3/4hp	6K					
	20	125	60	GP	6K					
	-	-	-	GP	-					
RSC-D	20	125	60	GP	6K	105	1/M	-/A	Note A2	
	16	250	60	GP	6K					
	-	125	60	1/3hp	6K					
	-	250	60	1/3hp	6K					
	-	125	60	3/4hp	6K					
	-	250	60	3/4hp	6K					
RSC-D2	20	125	60	GP	6K	65	1/M	-/A	Note A2, A3	
	16	125	60	GP	6K					
	16	250	60	GP	6K					
	-	125	60	1/4hp	6K					
	-	250	60	1/4hp	6K					
	-	250	60	3/4hp	6K					
RSC-H, RB1-H	20	125	60	GP	6K	105	1/M	-/A	Note A2	
	16	250	60	GP	6K					
	-	125	60	1/3hp	6K					
	-	250	60	1/3hp	6K					
	-	125	60	3/4hp	6K					
	-	250	60	3/4hp	6K					
RSC-X Series Where X denotes mfg.'s factory ID	16	125	60	1/4hp	6K	65	1/M	-/-	3	
	16	250	60	1/4hp	6K					
	20	125	60	3/4hp	6K					
	6.9	250	60	3/4hp	6K					
RSC1 Series	16	125	60	1/4hp	6K	65	1/M	-/-	3	

	16	250	60	1/4hp	6K				
	6.9	250	60	3/4hp	6K				
	20	125	60	GP	6K				
RV212, RV242, RV262, RV282, RV292	20	125	60	GP	6K	65	2/1	PP/-	-
	12	250	60	GP	6K				
RV213, RV243, RV263, RV283, RV293	20	125	60	GP	6K	65	1/2	-/-	-
	12	250	60	GP	6K				
RV216, RV246, RV266, RV286, RV296	20	125	60	GP	6K	65	2/2	PP/-	-
	12	250	60	GP	6K				
RV311, RV341, RV361, RV381, RV391	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
RV312, RV342, RV362, RV382, RV392	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
ST111	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST113, ST123, ST143, ST163	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST114, ST124, ST144, ST164	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST115, ST125, ST145, ST165	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST11C	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST11D	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST11M	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST11Z02	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST121	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST121D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST123D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST124D00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST125D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST12C	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				

ST12D	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST12DD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST12E	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST12M	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST12Z02	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST141	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST141D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST143D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST144D00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST144D10	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST145D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST145D10	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST14C	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST14D	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST14DD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST14DD10	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST14E	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST14M	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST14Z02	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST161	20	125	60	2hp	6K	85	M/M	PP/-	-

	15	277	60	2hp	6K				
ST161D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST163D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST164D00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST165D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST16C	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST16D	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST16DD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST16E	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST16M	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST16Z02	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST1W061D00	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
ST212, ST222, ST242, ST262	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST216, ST226, ST246, ST266	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST21E	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST21G, ST22G, ST24G, ST26G, ST1W065, ST1W061	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
ST21J	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST21K	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST222D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST226D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST22ED00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				

ST22GD00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST22J	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST22K	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST22KD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST242D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST246D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST24ED00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST24GD00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST24J	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST24JD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST24K	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST24KD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST24Z02D00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST262D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST266D00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST266D02	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST26ED00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST26GD00	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
ST26J	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
ST26K	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-

	15	277	60	1-1/2hp	6K					
ST26KD00	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
ST31R	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST31S	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST31T	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST32R	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST32S	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST32T	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST34R	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST34S	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST34T	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST36R	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST36S	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
ST36T	24	125	60	2hp	6K	85	3/M	-/-	-	
	15	277	60	2hp	6K					
WB24D	20	125	50/60	GP	6K	65	1/2	-/A	6	
	20	250	50/60	GP	6K					
	-	125	50/60	1-1/2hp	-					
	-	250	50/60	1-1/2hp	-					

Note - n/a

Note 1 - These switches will require testing for horsepower ratings in the end-use product.

Note 2 - HY15B and HY37B: The lock-off mechanism on these switches has been evaluated.

Note 3 - Wire leads may be provided with the switches. The suitability of the wire size, temperature and voltage rating shall be evaluated in the end product. Also a Temperature Test shall be conducted in the end product.

x - Refers to the color, which can be black (1) or white (2) for all switches

Marking: Company name or trademark      , catalog, model or part number, electrical ratings and the Recognized Component Mark,  on the product or on the smallest unit container in which the product is packaged.

Last Updated on 2023-10-02

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2023 UL LLC."