

## Switches, Appliance and Special Use Certified for Canada - Component

**COMPANY**

E-SWITCH INC, DBA LAMB INDUSTRIES

7153 NORTHLAND DR N.

BROOKLYN PARK, MN 55428 United States

E194579

Investigated to CAN/CSA-C22.2 No. 61058-1

Cat. No.	Load	Amps	Volts	Hz	Temp (°C)	Pol/ Cir	Endurance		Dis IP (mm)	SPCA	Std. Ed.	
							30C cycle	55C cycle				
<b>Appliance Switches "T125/55"</b>												
ST5 Series	R	16 PP	6-30	DC	T125/55	-1.4	6K	10K	40	micro	4A, 4B	-
	R	20 PP	6-30	DC	T125/55	-1.4	6K	10K	40			
	RM	16(8) PP	125/250	50- 60	T125/55	-1.4	6K	10K	40			
	RM	20(8) PP	125/250	50- 60	T125/55	-1.4	6K	10K	40			
<b>Appliance Switches "T55"</b>												
ST4 Series	-	PP	-	DC	55	-1.4	6K	10K	68	micro	-	-
	-	PP	-	DC	55	-1.4	6K	10K	-			
	GP	PP	-	50- 60	55	-1.4	6K	10K	-			
	GP	PP	-	50- 60	55	-1.4	6K	10K	-			
<b>Appliance Switches</b>												
14-RB1 Series	hp	3/4	125- 250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125- 250	60	55	1,2/1,2	6K	6K	-			
	RM	16(4)	125- 250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(8)	125- 250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125- 250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125- 250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125- 250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125- 250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125- 250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125- 250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
14-RB2 Series	hp	3/4	125- 250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125- 250	60	55	1,2/1,2	6K	6K	-			

	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(8)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125-250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125-250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
<b>14-RSC Series</b>	hp	3/4	125-250	60	55	1,2/1,2	6K	6K	40	-	-	-
	hp	1/3	125-250	60	55	1,2/1,2	6K	6K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(8)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	30(8)	125-250	50/60	55	1,2/1,2	-	10K	-			
	RM	30(8)	125-250	50/60	T125/55	1,2/1,2	-	10K	-			
	RM	16(8)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T125/55	1,2/1,2	6K	10K	-			
	R	16	30	DC	55	1,2/1,2	6K	10K	-			
	R	16	30	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	T125/55	1,2/1,2	6K	10K	-			
	R	16	48	DC	55	1,2/1,2	6K	10K	-			
	RC	8(128)	250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	55	1,2/1,2	6K	10K	-			
	RM	16(4)	125-250	50/60	T85/55	1,2/1,2	6K	10K	-			
	GP	20	125	50/60	65	1,2/1,2	-	6K	-			
	GP	20	125	50/60	105	1,2/1,2	-	6K	-			
<b>38-RB1 Series</b>	R	0~20	125	50/60	105	1/1,2	6K	10K	40	full 1.5	-	-
	R	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~20	125	50/60	105	1/1,2	6K	10K	-			
	hp	3/4	125	50/60	105	1/1,2	6K	10K	-			
<b>38-RB2 Series</b>	R	0~16	125	50/60	T105	1,2/1,2	6K	10K	40	full 1.5	-	-
	GP	0~16	125	50/60	T105	1,2/1,2	6K	10K	-			
	hp	3/4	125	50/60	T105	1,2/1,2	6K	10K	-			

<b>38-RSC Series</b>	R	0~20	125	50/60	105	1/1,2	6K	10K	40	full 1.5	-	-
	R	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~15	125	50/60	105	1/1,2	6K	10K	-			
	GP	0~20	125	50/60	105	1/1,2	6K	10K	-			
	hp	3/4	125	50/60	105	1/1,2	6K	10K	-			
<b>PP1-6</b>	GP	-	-	50-60	T55	1/2-2.2	6K	50K	40	micro	-	-
<b>PP1-7</b>	GP	-	-	50-60	T55	1/2-2.2	6K	50K	40	micro	-	-
<b>PR1 Series</b>	hp	3/4	250	50/60	105	1,2/1	6K	10K	40	full	-	-
	hp	1/2	125	50/60	105	1,2/1	6K	10K	-			
	GP	16	125	50/60	105	1,2/1	6K	10K	-			
	R	16	125	50/60	105	1,2/1	6K	10K	-			
<b>R7 f/b -1 or -2 f/b 3, f/b F,S or W, f/b Letter or Number. f/b Letter or Number. f/b Letter or Number. f/b Letter or Number. f/b -Letter or -Number. f/b Letter or Number.f/b A, B, D, 1, 2, 4, 7, 8 or 9. f/b -blank, -Letters or -Numbers</b>	-	-	-	DC	40T85/55	1/2-3.2	6K	10K	40	micro	-	-
	-	-	-	DC	T85/55	1/2-3.2	6K	10K	40			
	-	-	-	DC	40T85/55	2/2-3.4	6K	10K	67			
	-	-	-	DC	T85/55	2/2-3.4	6K	10K	67			
	-	-	-	DC	T55	1/2-3.2	6K	10K	40			
	-	-	-	DC	T55	2/2-3.4	6K	10K	40			
	-	-	-	DC	40T85/55	1/2-3.2	-	10K	67			
	-	-	-	DC	T85/55	1/2-3.2	-	10K	67			
	-	-	-	DC	40T85/55	2/2-3.4	-	10K	40			
	-	-	-	DC	T85/55	2/2-3.4	-	10K	40			
	-	-	-	DC	T55	1/2-3.2	-	10K	67			
	-	-	-	DC	T55	2/2-3.4	-	10K	67			
	GP	-	-	50-60	40T85/55	1/2-3.2	6K	10K	40			
	GP	-	-	50-60	T85/55	1/2-3.2	6K	10K	40			
	GP	-	-	50-60	40T85/55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T85/55	2/2-3.4	6K	10K	67			
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	-			
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	-			
	GP	-	-	50-60	40T85/55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	T85/55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	40T85/55	2/2-3.4	-	10K	-			
	GP	-	-	50-60	T85/55	2/2-3.4	-	10K	-			
	GP	-	-	50-60	T55	1/2-3.2	-	10K	-			
	GP	-	-	50-60	T55	2/2-3.4	-	10K	-			
<b>R7 f/b 1 or 2 f/b 1,2,4,5 or 8, f/b F,S or W, f/b letter, f/b letter or number, f/b Sxxx, f/b letter or number, f/b letter or number, f/b A,B,D,1,2,4,7,8 or 9, f/b letter or number, f/b letter or number, f/b letters or numbers</b>	R	16	30-6	DC	T55	1/1-1.2	6K	10K	-	micro	7A, 7B,7C, 7D. IP 40 for 40T85/55. IP 67 for T55	-
	R	16	30-6	DC	T55	1/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	1/1-1.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	1/2-2.2	6K	10K	-			
	RM	16(8)	125-250	50-60	T55	2/2-2.2	6K	10K	-			

	RM	16(8)	125-250	50-60	T55	2/2-2.4	6K	10K	-				
	RM	20(8)	125-250	50-60	T55	1/1-1.2	6K	10K	-				
	RM	20(8)	125-250	50-60	T55	1/2-2.2	6K	10K	-				
	RM	20(8)	125-250	50-60	T55	2/2-2.2	6K	10K	-				
	RM	20(8)	125-250	50-60	T55	2/2-2.4	6K	10K	-				
	R	16	30-6	DC	T55	2/2-2.2	6K	10K	-				
	R	16	30-6	DC	T55	2/2-2.4	6K	10K	-				
	R	16	30-6	DC	40T85/55	1/2, 2/2-2.2	6K	10K	-				
	R	16	30-6	DC	T85/55	1/2, 2/2-2.2	6K	10K	-				
	RM	16(8)	125-250	50-60	40T85/55	1/2, 2/2-2.2	6K	10K	-				
	RM	16(8)	125-250	50-60	T85/55	1/2, 2/2-2.2	6K	10K	-				
	RM	20(8)	125-250	50-60	40T85/55	1/2, 2/2-2.2	-	10K	-				
	RM	20(8)	125-250	50-60	T85/55	1/2, 2/2-2.2	-	10K	-				
<b>R7 f/b 1 or 2, f/b 6 or 7 f/b F,S or W, f/b letter, f/b letter or number, f/b Sxxx, f/b letter or number, f/b letter or number, f/b A,B,D,1,2,4,7,8 or 9, f/b letter or number, f/b letter or number, f/b letters or numbers.</b>	-	-	-	DC	T55	1/2-3.2	6K	10K	67	micro	-	-	-
	-	-	-	DC	T55	2/2-3.4	6K	10K	67				
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	67				
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	67				
	GP	-	-	50-60	T55	1/2-3.2	6K	10K	67				
	GP	-	-	50-60	T55	2/2-3.4	6K	10K	67				
	-	-	-	DC	40T85/55	1/2, 2/2-3.4	6K	10K	40				
	-	-	-	DC	T85/55	1/2, 2/2-3.4	6K	10K	40				
	GP	-	-	50-60	40T85/55	1/2, 2/2-3.4	6K	10K	40				
	GP	-	-	50-60	T85/55	1/2, 2/2-3.4	6K	10K	-				
	GP	-	-	50-60	40T85/55	1/2, 2/2-3.4	6K	10K	-				
	GP	-	-	50/60	T85/55	1/2, 2/2-3.4	6K	10K	-				
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
<b>RR1 followed by number, followed by 1, 3 or 5, followed by 3, maybe followed by alphanumeric/suffixes.</b>	GP	-	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	-	-	50/60	105	1,2/1,2	6K	10K	-				
<b>RR1 followed by number, followed by 1, 3 or 5, followed by C, maybe followed by alphanumeric/suffixes.</b>	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-				
<b>RR8 followed by number, followed by number or letter, followed by 3, maybe followed by alphanumeric/suffixes.</b>	GP	PP	-	50/60	105	1,2/1	6K	10K	40	full	-	-	-
	GP	PP	-	50/60	105	1,2/1	6K	10K	-				

RR8 followed by number, followed by number or letter, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1	6K	10K	-			
RRA followed by number, followed by number or letter, followed by 3, maybe followed by alphanumeric/suffixes.	GP	-	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-
	GP	-	-	50/60	105	1,2/1,2	6K	10K	-			
RRA followed by number, followed by number or letter, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
RRG3 followed by number, followed by 1, 3 or 5, followed by 3, maybe followed by alphanumeric/suffixes.	R	10	125	50/60	105	1,2/1,2	6K	10K	40	full	2A	-
	GP	10	125	50/60	105	1,2/1,2	6K	10K	40			
RRG3 followed by number, followed by 1, 3 or 5, followed by C, maybe followed by alphanumeric/suffixes.	GP	PP	-	50/60	105	1,2/1,2	6K	10K	40	full	-	-
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
	GP	PP	-	50/60	105	1,2/1,2	6K	10K	-			
<b>Micro</b>												
PP2	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-
PP2-2	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-
PP2-3	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-
PP2-4	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-
PP2-5	GP	-	-	50-60	T55	2/2-3.4	6K	50K	40	micro	-	-
<b>Push Button</b>												
HY106-6E7, HY106-6EB, HY106-6EC	RM	18(18)	250	50-60	55	2/1-1.3	6K	50K	40	full 4.0	Note B	2005-09-30
HY106-6Y7, HY106-6YB, HY106-6YC	RM	18(18)	250	50-60	55	2/2-2.2	6K	50K	40	full 4.0	Note B	2005-09-30
PA4 f/b none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C of J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8, f/b none or 1, f/b none, 0, 1, 2, 3, 4 or 5, f/b none, 3, 4, 5, 6 or 7	GP	16(4)	125	50-60	T125/55	1/1-1.2	6K	10K	-	full 3.1	6A, 8A, 8B, 8C	-
	GP	16(4) PP	125	50-60	T125/55	2/1-1.4	6K	10K	-			
	GP	16(8)	125	50-60	T125/55	1/1-1.2	6K	10K	-			
	GP	16(8) PP	125	50-60	T125/55	2/1-1.4	6K	10K	-			
	GP	16(4)	250	50-60	T125/55	1/1-1.2	6K	10K	-			
	GP	16(4) PP	250	50-60	T125/55	2/1-1.4	6K	10K	-			
	GP	16(8)	250	50-60	T125/55	1/1-1.2	6K	10K	-			
	GP	16(8) PP	250	50-60	T125/55	2/1-1.4	6K	10K	-			
	hp	1/4	125-250	60	T55	1/1,2/1	6K	6K	-			
	hp	3/4	125-250	60	T55	1/1,2/1	6K	6K	-			
PA5 f/b none or F, f/b 1 thru 6, 1, 4, 2 or E, f/b C or J	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40	full 3.1	-	-

	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	50-60	T125/55	1/1-1.2	6K	10K	40				
	GP	PP	-	50-60	T125/55	2/1-1.4	6K	10K	40				
	GP	-	-	60	T55	1/1,2/1	6K	6K	40				
	GP	-	-	60	T55	1/1,2/1	6K	6K	40				
<b>PB66</b>	RM	16(16)	127	50/60	T105/55	2/1-1.3	6K	50K	00	-	-	-	-
<b>ULP Followed by 12, followed by OA, followed by M1 or P1, followed by R, followed by SS, SF, PM or LS, followed by CL1 or OP1, followed by NIL, BLU, GRN, RED, YEL or RGB, followed by NIL, BLU, GRN, RED, YEL.</b>	R	0~0.1	0~28	DC	40T85	1/2-2.3	-	10K	40	full 0.8	1A	-	-
	R	0~0.1	0~28	DC	40T85	1/1-1.2	-	10K	-				
<b>Reversing Polarity</b>													
<b>ST34RE00</b>	GP	18(15) PP	125	50-60	55	M/M-1.6	6K	50K	-	full 1.5	6	-	-
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
<b>ST34SE00</b>	GP	PP	-	50-60	55	M/M-1.6	6K	50K	40	full 1.5	-	-	-
	GP	-	-	50/60	-	-	-	-	00				
	GP	-	-	50/60	-	-	-	-	00				
<b>ST34TE00</b>	GP	18(15) PP	125	50-60	55	M/M-1.6	6K	50K	-	full 1.5	6	-	-
	GP	-	-	-	-	-	-	-	-				
	GP	-	-	-	-	-	-	-	-				
<b>Rocker</b>													
<b>RA1 (3 Series)</b>	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/1,2	6K	10K	-				
<b>RA1 (C Series)</b>	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
<b>RA4 (3 Series)</b>	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/11,2	6K	10K	-				
<b>RA4 (C Series)</b>	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
<b>RA8 (3 Series)</b>	R	10 PP	125	50/60	105	1,2/1	6K	10K	40	full	-	-	-
	GP	10 PP	125	50/60	105	1,2/1	6K	10K	-				
<b>RA8 (C Series)</b>	hp	1/3 PP	125	50/60	105	1,2/1	6K	10K	40	full	-	-	-
	R	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1	6K	10K	-				
<b>RB5 Series</b>	RM	16(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	67	full	4A	-	-

	RM	20(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	-				
	RM	25(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	-				
	R	16	6~48	DC	T55	1,2/1,2-1.4	-	10K	-				
	R	20	6~36	DC	T55	1,2/1,2-1.4	-	10K	-				
<b>RD1 (3 Series)</b>	R	10 PP	125	50/60	105	1,2/1	6K	10K	40	full	-		-
	GP	10 PP	125	50/60	105	1,2/1	6K	10K	-				
<b>RD1 (C Series)</b>	hp	1/3 PP	125	50/60	105	1,2/1	6K	10K	40	full	-		-
	R	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1	6K	10K	-				
<b>RE1 (3 Series)</b>	R	10 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	GP	10 PP	125	50/60	105	1,2/1,2	6K	10K	-				
<b>RE1 (C Series)</b>	hp	1/3 PP	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	R	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	GP	16 PP	125	50/60	105	1,2/1,2	6K	10K	-				
	R	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
	GP	10 PP	250	50/60	105	1,2/1,2	6K	10K	-				
<b>RRGA (3 Series)</b>	R	10	125	50/60	105	1,2/1,2	6K	10K	40	full	-		-
	GP	10	125	50/60	105	1,2/1,2	6K	10K	-				
<b>ST121D00</b>	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6		-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-				
<b>ST123D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST124D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST125D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST12DD00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST141D00</b>	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6		-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-				
<b>ST143D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST144D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST144D10</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40				
<b>ST145D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-		-

	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST145D10</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST14DD00</b>	GP	18(12)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6	-
	GP	18(12)	125	50-60	55	1/2-3.2	6K	50K	-			
<b>ST14DD10</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST161D00</b>	GP	18(15)	125	50-60	55	1/1-1.2	6K	50K	-	full 1.5	6	-
	GP	18(15)	125	50-60	55	1/2-3.2	6K	50K	-			
<b>ST163D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST164D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST165D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST16DD00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST1W061D00</b>	GP	-	-	50-60	55	1/1-1.2	6K	50K	40	full 1.5	-	-
	GP	-	-	50-60	55	1/2-3.2	6K	50K	40			
<b>ST222D00</b>	GP	18(15) PP	125	50-60	55	2/2-2.4	6K	50K	-	full 1.5	6	-
	GP	18(15) PP	125	50-60	55	2/1-1.4	6K	50K	-			
<b>ST226D00</b>	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
<b>ST22ED00</b>	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
<b>ST22GD00</b>	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
<b>ST22KD00</b>	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
<b>ST242D00</b>	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
<b>ST246D00</b>	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			



ST24ED00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST24GD00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST24JD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST24KD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST24Z02D00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST262D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST266D00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST266D02	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST26ED00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
ST26GD00	GP	PP	-	50-60	55	2/2-2.4	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.4	6K	50K	40			
ST26KD00	GP	PP	-	50-60	55	2/2-3.6	6K	50K	40	full 1.5	-	-
	GP	PP	-	50-60	55	2/1-1.3	6K	50K	40			
<b>Rocker Switch</b>												
RB3 Series	RM	16(8)	125/250	50-60	T55	1,2/1,2-1.4	-	10K	67	full	4A	-
RBW2A	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
RBW2A Illuminated	RM	16(16)	125	50	T85/55	2/1-1.3	6K	50K	66	full	2, A, B, C, D	2005-09-30
	hp	1/3	125	50	T85/55	2/1-1.3	6K	50K	66			
RBW2B	hp	1/3	125	50	T85/55	2/2-1.3	6K	50K	66	full 2.0	A, B, C, D	2005-09-30
	RM	16(16)	125	50	T85/55	2/2-1.3	6K	50K	66			
PP27H12A2, PP27H12B2, PP27H12C2, PP27H12D2	RM	12(8)	127	50-60	T55	2/2-3.4	6K	50K	40	micro	17a	2005-09-30

Investigated to CSA-C22.2 No. 55

Cat. No.	Amps	Volts	Hz	Load	Endur- ance	Temp (°C)	POL/ THR	Circuit Code	SPCOA
HY11	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				

<b>HY12</b>	10	125	60	R	6K	65	2/1	-/-	3
	10	250	60	R	6K				
<b>HY15</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
<b>HY15B</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY15C</b>	18	125	60	GP	6K	65	M/M	PP/A	6 (12)
	12	250	60	GP	6K				
<b>HY18</b>	20	125	60	GP	6K	85	M/1	PP/-	-
	12	250	60	GP	6K				
<b>HY27</b>	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY27C</b>	16	125	60	GP	6K	65	2/1	PP/-	6 (12), Note 2
	12	250	60	GP	6K				
<b>HY30</b>	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
<b>HY34</b>	6	125	60	GP	6K	65	1/1	-/-	6
	3	250	60	GP	6K				
<b>HY37</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
<b>HY37B</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
<b>HY37C</b>	17	125	60	GP	6K	65	2/1	PP/-	Note 2
	12	250	60	GP	6K				
<b>HY38</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY38B</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY38C</b>	24	125	60	2hp	6K	65	2/1	-/-	6 (12)
	12	250	60	2hp	6K				
<b>HY42</b>	6	125	60	GP	6K	105	1/1	-/-	6 (18)
	3	250	60	GP	6K				
	1	125	DC	T	6K				
	6	125	60	L	6K				
<b>HY7-11D, HY7-41D, HY7-61D, HY7-81D, HY7-91D</b>	20	125	60	GP	6K	65	1/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
<b>HY7-12D, HY7-42D, HY7-62D, HY7-82D, HY7-92D</b>	20	125	60	GP	6K	65	2/1	-/-	-
	12	250	60	GP	6K				
	10	125	60	R	6K				
	10	250	60	R	6K				
<b>LSU11 Series</b>	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
<b>PA series</b>	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-
	16	250	60	GP	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>PA4 Followed by none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8, f/b 1, f/b 0 thru 5, f/b 3 thru 7.</b>	16	125	60	GP	6K	65	1/1 or 2/1	PP/A or D1	A2
	16	250	60	GP	6K				

	-	125	60	3/4hp	6K					
	-	250	60	3/4hp	6K					
	12	125	60	GP	6K					
	12	250	60	GP	6K					
	-	125	60	1/4hp	6K					
	-	250	60	1/4hp	6K					
<b>PA4 Followed by none, R or C, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J, f/b 1, 2, 4 or 9, f/b 0 thru 9, f/b 0, 1, 2 or 8, f/b 0 thru 8.</b>	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-	
	16	250	60	GP	6K					
	-	125	60	3/4hp	6K					
	-	250	60	3/4hp	6K					
	12	125	60	GP	6K					
	12	250	60	GP	6K					
	-	125	60	1/4hp	6K					
	-	250	60	1/4hp	6K					
<b>PA5 Followed by none or F, f/b 1 thru 6, f/b 1, 4, 2 or E, f/b C or J.</b>	16	125	60	GP	6K	65	1/1or2/1	PP/A or D	-	
	16	250	60	GP	6K					
	-	125	60	3/4hp	6K					
	-	250	60	3/4hp	6K					
	12	125	60	GP	6K					
	12	250	60	GP	6K					
	-	125	60	1/4hp	6K					
	-	250	60	1/4hp	6K					
<b>PP1-1T7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-	
	16	125	50/60	1hp	6K					
<b>PP1-DB7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-	
	16	125	50/60	1hp	6K					
<b>PP1-DT7-xBx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-	
	16	125	50/60	1hp	6K					
<b>PP1-EB7-xBx, PP1-EB7-xDx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-	
	16	125	50/60	1hp	6K					
<b>PP1-FB7-xDx</b>	12	250	50/60	1hp	6K	85	1/2	-/-	-	
	16	125	50/60	1hp	6K					
<b>PP2-1H7-xAx</b>	12	250	60	1hp	6K	85	2/2	-/-	-	
	16	250	60	1hp	6K					
<b>PP2-1U7-xBx</b>	12	250	60	1hp	6K	85	2/2	-/-	-	
	16	250	60	1hp	6K					
<b>PP2-4H7-xAx</b>	12	250	60	1hp	6K	85	2/2	-/-	-	
	16	250	60	1hp	6K					
<b>PP2-4U7-xBx</b>	12	250	60	1hp	6K	85	2/2	-/-	-	
	16	250	60	1hp	6K					
<b>PP2-4U7-xCx</b>	12	250	60	1hp	6K	85	2/2	-/-	-	
	16	250	60	1hp	6K					
<b>PR Series</b>	16	125	60	GP	6K	105	2/2	-/-	2	
	-	250	60	3/4hp	6K					
	-	125	60	1/2hp	6K					
<b>QKS-1</b>	12	125	60	GP	6K	65	2/1	PP/-	Note 1	
	8	250	60	GP	6K					
<b>QKS-5</b>	12	125	60	GP	6K	65	2/1	PP/-	Note 1	
	8	250	60	GP	6K					
<b>RA1</b>	16	125	60	GP	6K	105	1/1,1/2	-/-	-	
	10	125	60	GP	6K					

	10	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA1-A, ww/o suffix letters and numbers</b>	11	125	60	GP	6K	55	2/M	-/-	-
	5.5	250	60	GP	6K				
<b>RA1-E ww/o suffix letters and numbers</b>	16	125	60	R	6K	55	M/1	PP/-	Note A1
<b>RA2 Series</b>	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA4 Series</b>	10	125	60	GP	6K	105	2/1,2/2	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA7 w/wo suffix letters and/or numbers, SP</b>	16	125	60	R	6K	55	1/1	-/-	A1
<b>RA8 Series, RR8 Series</b>	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RA8-E ww/o suffix letters and numbers</b>	16	125	60	R	6K	55	M/1	PP/-	Note A1
<b>RA9 w/wo suffix letters and/or numbers, DP, SP</b>	16	125	60	R	6K	55	2/1	PP/-	A1
<b>RB1</b>	15	125	60	GP	6K	85	1/1,1/2	-/-	-
	7.5	250	60	GP	6K				
<b>RB1-D</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RB1-E</b>	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
<b>RB2-C</b>	16	125	60	GP	6K	85	2/1, 2/2	-/-	2, 3
	8	250	60	GP	6K				
<b>RB2-D</b>	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RB2-E</b>	16	125	60	GP	6K	65	1/M	-/-	A2,A3
	16	250	60	GP	6K				
<b>RB2-H Series</b>	20	125	60	GP	6K	105	M/M	PP/A/PP/D1	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RC SERIES</b>	20	125	60	GP	12K	85	1/1	-/-	2, 3
	16	250	60	GP	12K				

	6	120	60	L	12K				
	-	250	60	3/4hp	12K				
<b>RD-Series</b>	10	125	60	GP	6K	105	1/1,2/1	-/-	-
	10	250	60	GP	6K				
	16	125	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
<b>RE1-Series</b>	10	125	60	1/3hp	6K	105	1/2	PP/-	-
	10	250	60	1/3hp	6K				
	16	125	60	GP	6K				
<b>RF-SERIES</b>	16	125	60	GP	6K	105	2/1	PP/-	-
	-	125	60	1/2hp	6K				
	-	250	60	1/2hp	6K				
<b>RR Series</b>	10	125	60	1/3hp	6K	105	1/1	PP/-	-
	10	250	60	1/3hp	6K				
	16	125	60	GP	6K				
<b>RR5</b>	20	125	60	GP	6K	65	1/M	-/-	Note 3
	12	250	60	GP	6K				
	12	125	60	GP	6K				
	10	250	60	GP	6K				
	10	125	60	GP	6K				
	6	250	60	GP	6K				
	6	125	60	GP	6K				
	3	250	60	GP	6K				
<b>RRA Series</b>	10	125	60	1/3hp	-	-	-	-/-	-
	10	250	60	1/3hp	-				
	15	125	60	GP	-				
<b>RSC Series</b>	15	125	60	GP	6K	105	1/1,1/2	-/-	-
	-	125	60	3/4hp	6K				
	20	125	60	GP	6K				
	-	-	-	GP	-				
<b>RSC-D</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-D2</b>	20	125	60	GP	6K	65	1/M	-/A	Note A2, A3
	16	125	60	GP	6K				
	16	250	60	GP	6K				
	-	125	60	1/4hp	6K				
	-	250	60	1/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-H, RB1-H</b>	20	125	60	GP	6K	105	1/M	-/A	Note A2
	16	250	60	GP	6K				
	-	125	60	1/3hp	6K				
	-	250	60	1/3hp	6K				
	-	125	60	3/4hp	6K				
	-	250	60	3/4hp	6K				
<b>RSC-X Series Where X denotes mfg.'s factory ID</b>	16	125	60	1/4hp	6K	65	1/M	-/-	3
	16	250	60	1/4hp	6K				

	20	125	60	3/4hp	6K					
	6.9	250	60	3/4hp	6K					
<b>RSC1 Series</b>	16	125	60	1/4hp	6K	65	1/M	-/-		3
	16	250	60	1/4hp	6K					
	6.9	250	60	3/4hp	6K					
	20	125	60	GP	6K					
<b>RV212, RV242, RV262, RV282, RV292</b>	20	125	60	GP	6K	65	2/1	PP/-		-
	12	250	60	GP	6K					
<b>RV213, RV243, RV263, RV283, RV293</b>	20	125	60	GP	6K	65	1/2	-/-		-
	12	250	60	GP	6K					
<b>RV216, RV246, RV266, RV286, RV296</b>	20	125	60	GP	6K	65	2/2	PP/-		-
	12	250	60	GP	6K					
<b>RV311, RV341, RV361, RV381, RV391</b>	20	125	60	GP	6K	65	1/1	-/-		-
	12	250	60	GP	6K					
	10	125	60	R	6K					
	10	250	60	R	6K					
<b>RV312, RV342, RV362, RV382, RV392</b>	20	125	60	GP	6K	65	2/1	-/-		-
	12	250	60	GP	6K					
	10	125	60	R	6K					
	10	250	60	R	6K					
<b>ST111</b>	20	125	60	2hp	6K	85	M/M	PP/-		-
	15	277	60	2hp	6K					
<b>ST113, ST123, ST143, ST163</b>	20	125	60	2hp	6K	85	M/M	PP/-		-
	15	277	60	2hp	6K					
<b>ST114, ST124, ST144, ST164</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-		-
	15	277	60	1-1/2hp	6K					
<b>ST115, ST125, ST145, ST165</b>	20	125	60	2hp	6K	85	M/M	PP/-		-
	15	277	60	2hp	6K					
<b>ST11C</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-		-
	15	277	60	1-1/2hp	6K					
<b>ST11D</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-		-
	15	277	60	1-1/2hp	6K					
<b>ST11M</b>	20	125	60	2hp	6K	85	M/M	PP/-		-
	15	277	60	2hp	6K					
<b>ST11Z02</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-		-
	15	277	60	1-1/2hp	6K					
<b>ST121</b>	20	125	60	2hp	6K	85	M/M	PP/-		-
	15	277	60	2hp	6K					
<b>ST121D00</b>	20	125	60	2hp	6K	85	1/M	-/-		-
	15	277	60	2hp	6K					
<b>ST123D00</b>	20	125	60	2hp	6K	85	1/M	-/-		-
	15	277	60	2hp	6K					
<b>ST124D00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-		-
	15	277	60	1-1/2hp	6K					
<b>ST125D00</b>	20	125	60	2hp	6K	85	1/M	-/-		-
	15	277	60	2hp	6K					

<b>ST12C</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST12D</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST12DD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST12E</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST12M</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST12Z02</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST141</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST141D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST143D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST144D00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST144D10</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST145D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST145D10</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST14C</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST14D</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST14DD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST14DD10</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST14E</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST14M</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				

<b>ST14Z02</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST161</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST161D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST163D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST164D00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST165D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST16C</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST16D</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST16DD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST16E</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST16M</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST16Z02</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST1W061D00</b>	20	125	60	2hp	6K	85	1/M	-/-	-
	15	277	60	2hp	6K				
<b>ST212, ST222, ST242, ST262</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST216, ST226, ST246, ST266</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST21E</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST21G, ST22G, ST24G, ST26G, ST1W065, ST1W061</b>	20	125	60	2hp	6K	85	M/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST21J</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST21K</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST222D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-
	15	277	60	2hp	6K				
<b>ST226D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-



	15	277	60	2hp	6K					
<b>ST22ED00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST22GD00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST22J</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST22K</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST22KD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST242D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST246D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST24ED00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST24GD00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST24J</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST24JD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST24K</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST24KD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST24Z02D00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST262D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST266D00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST266D02</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					
<b>ST26ED00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-	
	15	277	60	1-1/2hp	6K					
<b>ST26GD00</b>	20	125	60	2hp	6K	85	2/M	PP/-	-	
	15	277	60	2hp	6K					

<b>ST26J</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST26K</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST26KD00</b>	20	125	60	1-1/2hp	6K	85	M/M	PP/-	-
	15	277	60	1-1/2hp	6K				
<b>ST31R</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST31S</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST31T</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST32R</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST32S</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST32T</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST34R</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST34S</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST34T</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST36R</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST36S</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>ST36T</b>	24	125	60	2hp	6K	85	3/M	-/-	-
	15	277	60	2hp	6K				
<b>WB24D</b>	20	125	50/60	GP	6K	65	1/2	-/A	6
	20	250	50/60	GP	6K				
	-	125	50/60	1-1/2hp	-				
	-	250	50/60	1-1/2hp	-				

Note - n/a

Note 1 - These switches will require testing for horsepower ratings in the end-use product.

Note 2 - HY15B and HY37B: The lock-off mechanism on these switches has been evaluated.

Note 3 - Wire leads may be provided with the switches. The suitability of the wire size, temperature and voltage rating shall be evaluated in the end product. Also a Temperature Test shall be conducted in the end product.

x - Refers to the color, which can be black (1) or white (2) for all switches

Marking: Company name or trademark  E-SWITCH®  LAMB  LAMB  LAMB INDUSTRIES, catalog, model or part number, electrical ratings and the Recognized Component Mark for Canada,  on the product or on the smallest unit container in which the product is packaged.

Last Updated on 2023-10-02

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2023 UL LLC."